

iT600 Coordinator Update Software Installation Guide

1. Download Instructions

- Access official download portal: <u>https://saluscontrols.com/dk/hjaelp-og-downloads/</u>
- Navigation path: Downloads → Coordinator Tools → SALUS_EU_Coordinator_Upgrade_Tool_er_boxed.exe
- File Verification:
 - Filename: SALUS_EU_Coordinator_Upgrade_Tool_er_boxed.exe (Windows)
 - SHA-256: 7a3b8d... (MAC)

saluscontrols.com/dk/hiaelo-og-downloa	ids/			
کڅ۷۲۲۵۵ ۵۰ ه ه	rodukter Til installatører	Forhandlere 👻 Hjælp og downl	loads Blog Teknisk support	Om os Q
	OFTE STI	LLEDE SPØ	RGSMÅL	
TRV10RFM RADIATORVENTIL	UGE600 GATEWAY	SP600 SMART STIK	Udstyr og One Touch	Smart Home appen
HVILKE BATTERIER SKAL J	EG BRUGE?			O
MIN TRV10RFM LYSER PER	RMANENT RØDT.			٢
MIN TRV10RFM REAGERED	R IKKE ALTID MED DET SAMN	IE.		O
COORDINATOR UPDATE PC download Opdater dit trådløse gulvvarmesystem (KL08RF) med den software, der kan downloades på din pc eller Mac. MAC download				

• File Details: SALUS_EU_Coordinator_Upgrade_Tool_er_boxed (Windows Installer Package)



iT600 Coordinator Update Software Installation Guide

2. Installation Procedure

Windows:

- 1. Disable antivirus temporarily (optional but recommended)
 - Run installer as Administrator:
- SALUS_EU_Coordinator_Upgrade_Tool_er_boxed

2. Follow installation wizard: Welcome Screen: Click Next →



Installation Confirmation: Click Install →





Progress: Wait for completion \rightarrow



Finalize setup:

- Click the "Finish" button to exit the Setup Wizard and launch the Tool from desktop.
- Click "Run" button to launch Salus EU Coordinator Upgrade Tool.





macOS:

- 1. Right-click .dmg \rightarrow Open (bypass Gatekeeper)
- 2. Drag icon to Applications folder

3. Launching the Tool

- Open via desktop shortcut or Start menu.
- Initial Interface: Ensure the coordinator is disconnected at this stage.

7//		
	Welcome to your Coordinator Firmware Update Tool	
	Please click start to begin	
	START	



4. App Update Process – iT600 Coordinator Update Tool

1. Version Check:

> iT600 Coordi	inator Update Tool v1.5
7/	
	Checking for the latest Version of the Coordinator Update Tool
	CANCEL

2. Update Initiation:

• Click Update





3. Progress Monitoring:

• Coordinator Update Tool is downloading and updating.

Dov	Vnloading and Updating Software	
	Please wait	
	68%	
		антана 1997 — Полоникана 1997 — Полоникана 1997 — Полоникана
	CANCEL	

4. Completion:

• "Update successful!" message appears.

S 11600 Coordinator Update Tool v1.5
The Coordinator Firmware Update
Tool is now up to date
Plug your Coordinator into a USB port
and click next to check your Coordinator
NEXT

5. Firmware Update Process – Updating the coordinator

1. Version Check:

- Ensure that Bluetooth is disabled on laptop/PC. Open Windows Settings → Bluetooth & devices → Toggle Bluetooth OFF.
- Plug the Coordinator into a USB port.
- Click **NEXT** to check Coordinator.



• If Bluetooth is disconnected and CO10 is not found, please click Install Driver.

J Coordinator	Update Tool v4.0 (Svarer ikke)
	Sevena.
	Searching for coordinator
	Cannot search the CO10RF?

2. Update Initiation:

• Click Update

Firmware Update required	
Click below to update the coordinator	
Current coordinator version is 0151 New coordinator version is 0152	
CANCEL UPDATE	

3. Progress Monitoring:

• Critical! Removing the coordinator or switching your computer off will cancel the update.

55		S.
Updating the o	Coordinator	Firmware
	0%	
Warning! Removing your computer of	the coordinate	or or switching he update

4. Completion:

- "Update successful!" message appears.
- Coordinator reboots automatically.

iT600 System Firm	nware Upgrade v3.3	—
	Firmware update successful	
	It is now safe to unplug the coordinator	
Please nev	allow 48 hours for the Coordinator to upda w firmware to all other devices on the syste	te the em
com:	CLOSE	

6. Key Troubleshooting Steps

Issue: COM port conflicts (e.g., COM5/COM6 appear but tool fails).

Solution:

1. Disable Bluetooth: Open Windows Settings → Bluetooth & devices → Toggle Bluetooth OFF.

2. Check COM ports: Open Device Manager \rightarrow Ports (COM & LPT). Verify if COM5/COM6 disappeared.

3. Relaunch tool: If conflicting ports vanished, reconnect coordinator and retry update.

Error-Specific Solutions

Error Message	Resolution Steps
"Signature verification failed"	Re-download installer (file corruption)
"Update timed out"	Disable firewall/VPN \rightarrow Retry in Safe Mode
Application crash on launch	Install latest .NET Framework + VC++ Redist